

Reaper Nano VTX



特点:

1. 滤波纯净，抗干扰性能优异，全油门画面依然稳定。
2. 杂散小。
3. 不飘频。
4. 尺寸小，功率高。
5. 超低功耗。

规格:

1. 尺寸: 12 × 16mm
2. 连接口: UFL
3. 显示灯: 3颗LED
4. 重量: <1g
5. 功率: 25/100/200/350mW
6. 输入: 5V
7. 输出: 5V
8. 通道: 40CH
9. 遥控器协议: Tramp

1.LED灯说明

LED	说明
红灯	功率
绿灯	频段
蓝灯	通道

2.按键操作方法

长按3秒，进入频段设置，短按设置不同频段；
再长按3秒，进入通道设置，短按设置不同通道；
继续长按3秒，进入功率设置，短按设置不同功率。

3.频率表

Band	CH1	CH2	CH3	CH4	CH5	CH6	CH7	CH8
Band A	5865	5845	5825	5805	5785	5765	5745	5725
Band B	5733	5752	5771	5790	5809	5828	5847	5866
Band E	5705	5685	5665	5645	5885	5905	5925	5945
Band F	5740	5760	5780	5800	5820	5840	5860	5880
Band R	5658	5695	5732	5769	5806	5843	5880	5917

Reaper Nano VTX



Features:

1. Amazingly clean filtering, great interference rejection ability.
2. Small Spur.
3. No frequency drift.
4. Small size, high power.
5. Low consumption.

Spec:

1. Size: 12×16mm
2. Connector: UFL
3. Display: 3LED
4. Weight: <1g
5. Power: 25/100/200/350mW
6. Input: 5V
7. Output: 5V
8. Channel: 40CH
9. Protocol: Tramp

1.LED

LED	Description
Red	Power
Green	Band
Blue	Channel

2.Button Operation

Band select mode:

Press button for an additional 3s, enter BAND setup, GREEN LED on and flash, select band by simple short presses

Channel select mode:

Continue to press the button for 3s, enter CHANNEL setup, all 3 LED are on and flash, select channel by simple short presses.

Power select mode:

Continue to press the button for 3s, enter POWER setup, RED LED is on and flash, select power by simple short presses.

3.Frequency Table

Band	CH1	CH2	CH3	CH4	CH5	CH6	CH7	CH8
Band A	5865	5845	5825	5805	5785	5765	5745	5725
Band B	5733	5752	5771	5790	5809	5828	5847	5866
Band E	5705	5685	5665	5645	5885	5905	5925	5945
Band F	5740	5760	5780	5800	5820	5840	5860	5880
Band R	5658	5695	5732	5769	5806	5843	5880	5917